# 4BT3.3-G6

# **Emissions Compliance:** EPA Tier2 (TPEM) at 60 Hz



# > Specification sheet

# Currining

## Our energy working for you.™

# **Description**

The B3.3 has all the strength and reliability the genset industry has come to expect from the B Series range but in a smaller, lighter and more economical package. The B3.3 features direct fuel injection, resulting in cleaner, quieter and more fuel efficient performance. With a highly compact 4 cylinder envelope and extremely low heatrejection, the engine offers a high degree of installation flexibility.



This engine has been built to comply with CE certification.



This engine has been designed in facilities certified to ISO9001 and manufactured in facilities certified to ISO9001 or ISO9002.

#### **Features**

**Bosch-Zexel VE** - Direct injection in-line pump for cleaner, more efficient fuel consumption.

**Parent Bore Block** - Deep, stiff crankcase and optimised rib arrangement to enhance strength and reduce noise.

**12 volt electrics package** as standard, with starter, alternator and fuel solenoid.

Minimal derate for high altitude or high ambient applications.

Shallow oil pan and single spin-on oil filter.

SAE '4' flywheel housing.

**Integrated Design** - Each component has been specifically developed and rigorously tested for G-Drive products, ensuring high performance, durability and reliability.

**Service and Support** - G-Drive products are backed by an uncompromising level of technical support and after sales service, delivered through a world class service network.

## **1500 rpm (50 Hz Ratings)**

Gross Engine Output			Net	Engine Out	put	Typical Generator Set Output					
Standby	Prime	Base	Standby	Prime	Base	Standby (ESP)		Prime (PRP)		Base (COP)	
kWm/BHP				kWm/BHP		kWe	kVA	kWe	kVA	kWe	kVA
51/68	46/63	37/50	49/66	44/59	36/48	44	55	40	50	32	40

#### 1800 rpm (60 Hz Ratings)

Gross Engine Output			Net	Engine Out	put	Typical Generator Set Output					
Standby	Prime	Base	Standby	Prime	Base	Standby (ESP)		Prime (PRP)		Base (COP)	
kWm/BHP				kWm/BHP		kWe	kVA	kWe	kVA	kWe	kVA
61/82	54/73	43/58	59/79	53/71	42/56	50	63	45	56	35	44

Our energy working for you.™



# **General Engine Data**

Type	4 cycle, in-line, turbocharged			
Bore mm	95 mm (3.74 in.)			
Stroke mm	115 mm (4.53 in.)			
Displacement Litre	3.3 litre (199 in. <sup>3</sup> )			
Cylinder Block	Cast iron, 4 cylinder			
Battery Charging Alternator	45 amps			
Starting Voltage	12 volt, negative ground			
Fuel System	Direct injection			
Fuel Filter	Spin-on fuel filters with water separator			
Lube Oil Filter Type(s)	Spin-on full flow filter			
Lube Oil Capacity (I)	7.5			
Flywheel Dimensions	4/11			

# **Coolpac Performance Data**

Caaling Custom Design	ı
Cooling System Design	
Coolant Ratio	
Coolant Capacity (I)	
Limiting Ambient Temp.**	ı
Fan Power	
Cooling System Air Flow (m <sup>3</sup> /s)**	
Air Cleaner Type	
** @ 13 mm H <sup>2</sup> 0	

Not Available

# **Ratings Definitions**

#### **Emergency Standby Power (ESP):**

Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. Emergency Standby Power (ESP) is in accordance with ISO 8528. Fuel Stop power in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.

#### Limited-Time Running Power (LTP):

Applicable for supplying power to a constant electrical load for limited hours. Limited-Time Running Power (LTP) is in accordance with ISO 8528.

#### Prime Power (PRP):


Applicable for supplying power to varying electrical load for unlimited hours. Prime Power (PRP) is in accordance with ISO 8528. Ten percent overload capability is available in accordance with ISO 3046, AS 2789, DIN 6271 and BS 5514.

#### Base Load (Continuous) Power (COP):

Applicable for supplying power continuously to a constant electrical load for unlimited hours. Continuous Power (COP) in accordance with ISO 8528, ISO 3046, AS 2789, DIN6271 and BS 5514.

# **Weight & Dimensions**

Length	Width	Height	Weight (dry)
mm	mm	mm	kg
838	622	814	265



# Fuel Consumption 1500 (50 Hz)

%	kWm	BHP	L/ph	US gal/ph					
Standby Power									
100	51	68	15	4					
Prime Power									
100	46	63	13	3.5					
75	35	48	N/A	N/A					
50	23	32	N/A	N/A					
25	12	16	N/A	N/A					

# Fuel Consumption 1800 (60 Hz)

%	kWm	BHP	L/ph	US gal/ph					
Standby Power									
100	61	82	17	4.4					
Prime Power	Prime Power								
100	54	73	15	4					
75	41	55	11	2.8					
50	27	37	7	1.9					
25	14	18	4	1.1					

#### **Cummins G-Drive Engines**

**Asia Pacific** 10 Toh Guan Road #07-01 Singapore 608838

TT International Tradepark Phone 65 6417 2388 Fax 65 6417 2399

Europe, CIS, Middle **East and Africa** Manston Park Columbus Ave Manston Ramsgate

Kent CT12 5BF, UK Phone 44 1843 255000 Fax 44 1843 255902

Latin America Rua Jati, 310, Cumbica Guarulhos, SP 07180-900

Brazil Phone 55 11 2186 4552 Fax 55 11 2186 4729

Cummins S. de R.L. de C.V. Eje 122 No. 200 Zona Industrial San Luis Potosí, S.L.P. 78090 Mexico

Phone 52 444 870 6700 Fax 52 444 870 6811

**North America** 

1400 73rd Avenue N.E. Minneapolis, MN 55432 USA Phone 1 763 574 5000 USA Toll-free 1 877 769 7669 Fax 1 763 574 5298

#### Our energy working for you.™

